

## Item description

**Orbis Timesaver Relay Base**

Type	Art.no.
B03560-00	59.761.06

## Description

- The relay socket includes a potential-free changeover contact for switching external devices. When the fire alarm goes to alarm, a voltage is applied to the relay, causing the contact to change state. The contact remains in the state until the fire alarm is reset.
- Mounting holes with two different hole distances
- LED-alignment mark
- Mechanical security mechanism
- Pass-through bridge for voltage testing of the zone wiring prior to commissioning
- Switching capacity up to 30 V at 1 A
- Tested according to EN 54-7, EN 50155, EN 50121-3, EN 60068, EN 61373, EN 45545-2 (HL3)



## Technical data

Operating voltage:	8,5 – 33 V DC
Quiescent current:	95 $\mu$ A
Alarm current	40 mA at 24V
Temperature range:	-40°C to +70°C
Relative humidity:	max 98%
Housing:	Polycarbonate
Colour:	white (similar RAL 9003)
Dimensions ( $\varnothing$ x height):	100mm x 15 mm
Weight:	60 g